

Product Information																			
Product Description:	7.0" USB Touchscreen monitor																		
Model Name:	MIMO UM-760CF																		
Model Type:	VESA mount																		
Product picture		Product Specifications																	
		Product Features																	
		<ul style="list-style-type: none"> - High Speed USB2.0 Powered / Interfaced (USB Plug & Play) - Capacitive Touchscreen Panel - Bright, Vibrant, High-resolution LCD Display - High Gloss Black Finish, Stylish Design - Swivel the monitor anytime to suit your application - Instant Extension / Mirror Display Mode Support - Low-Energy Efficient Mini-Display to set up various applications; Program Icons, E-Mail Checking, Incoming Phone Numbers, Car-pc monitor, Screen of Point of sale for Customers, Secondary Screen for use in industrial monitoring ... etc. 																	
		Technical Data																	
		<table border="1"> <tr> <td rowspan="5">Display</td> <td>Screen Size</td> <td>7.0"</td> </tr> <tr> <td>Resolution</td> <td>WSVGA (1024x600)</td> </tr> <tr> <td>Brightness</td> <td>250 cd/m²</td> </tr> <tr> <td>Contrast Ratio</td> <td>700:1</td> </tr> <tr> <td>Response Time</td> <td>10 msec</td> </tr> </table>	Display	Screen Size	7.0"	Resolution	WSVGA (1024x600)	Brightness	250 cd/m ²	Contrast Ratio	700:1	Response Time	10 msec	<table border="1"> <tr> <td rowspan="3">Signal Input</td> <td>Touch Input</td> <td>Capacitive Touchscreen Panel</td> </tr> <tr> <td>Video Input</td> <td>USB2.0 High Speed</td> </tr> <tr> <td>Connector</td> <td>USB Mini B Type</td> </tr> </table>	Signal Input	Touch Input	Capacitive Touchscreen Panel	Video Input	USB2.0 High Speed
Display	Screen Size	7.0"																	
	Resolution	WSVGA (1024x600)																	
	Brightness	250 cd/m ²																	
	Contrast Ratio	700:1																	
	Response Time	10 msec																	
Signal Input	Touch Input	Capacitive Touchscreen Panel																	
	Video Input	USB2.0 High Speed																	
	Connector	USB Mini B Type																	
<table border="1"> <tr> <td rowspan="2">Power</td> <td>Power Input</td> <td>USB Power (5V, current depending on brightness setting, 400mA-900mA) *</td> </tr> <tr> <td>Power Consumption</td> <td>2.0 ~ 4.5W*</td> </tr> </table>	Power	Power Input	USB Power (5V, current depending on brightness setting, 400mA-900mA) *	Power Consumption	2.0 ~ 4.5W*	<table border="1"> <tr> <td>Feature</td> <td>UI, Pivot</td> <td>VESA75 Compatible</td> </tr> </table>	Feature	UI, Pivot	VESA75 Compatible										
Power		Power Input	USB Power (5V, current depending on brightness setting, 400mA-900mA) *																
	Power Consumption	2.0 ~ 4.5W*																	
Feature	UI, Pivot	VESA75 Compatible																	
		<table border="1"> <tr> <td rowspan="4">PC Requirement</td> <td>Processor</td> <td>Intel Pentium/Celeron/AMD/K6/Athlon/Duron 1.2GHz or above</td> </tr> <tr> <td>RAM</td> <td>512MB or above</td> </tr> <tr> <td>HDD</td> <td>30MB HDD space above</td> </tr> <tr> <td>OS</td> <td>Windows Xp/7/8/10 Mac supported</td> </tr> </table>	PC Requirement	Processor	Intel Pentium/Celeron/AMD/K6/Athlon/Duron 1.2GHz or above	RAM	512MB or above	HDD	30MB HDD space above	OS	Windows Xp/7/8/10 Mac supported								
		PC Requirement		Processor	Intel Pentium/Celeron/AMD/K6/Athlon/Duron 1.2GHz or above														
				RAM	512MB or above														
				HDD	30MB HDD space above														
			OS	Windows Xp/7/8/10 Mac supported															
Size		185(W) x 145(H) x 120(D) mm																	
Weight		267g																	
https://www.lcdstore.de/MIMO-Monitore/7-Zoll																			

* A USB 2.0 interface of a PC, laptop or tablet, is specified to allow a current of 500 mA to supply a device connected to that USB-connection. PCs typically supply a higher current, so a MIMO normally can work on one USB connection of a PC. Laptops and especially tablets are designed for low power consumption, so the current specification of the USB interface typically is not outperformed, but in many cases not met.

It that case we recommend to use an Y-cable to connect two USB interfaces. Two adjacent connectors are the best choice to reduce compensating currents between the two USB connections.

A power supply with an USB connector linked to the Y-cable is the second best choice to achieve the necessary supply current. Due to a possible higher voltage difference between the USB connector of the host and the power supply compensating currents are more likely, which probably can damage the USB interface of the host.

The USB-A connector of the included USB cable also fits a USB-A connector of USB 3.0 (blue connector core). USB 3.0 is specified to supply 900mA.